

Specifications

WLAN Features

- **Wireless Standards:**
IEEE 802.11ax/ac/n/a 5 GHz,
IEEE 802.11ax/n/g/b 2.4 GHz
- **Signal Rate:**
5 GHz
11ax: Up to 2402Mbps(dynamic)
11ac: Up to 1732Mbps(dynamic)
11n: Up to 300 Mbps(dynamic)
11a: Up to 54 Mbps(dynamic)
2.4 GHz
11ax: Up to 574 Mbps(dynamic)
11n: Up to 400 Mbps(dynamic)
11g: Up to 54 Mbps(dynamic)
11b: Up to 11 Mbps(dynamic)
- **Reception Sensitivity:**
5 GHz :
11ac VHT 20M MCS: -93 dBm
11ax HE 80M MCS11: -58 dBm
11ax HE 160M MCS11: -64dBm

2.4 GHz :
11n HT20M MSC0: -96 dBm
11ax HE40M MSC11: -65dBm
- **Wireless Modes:** Infrastructure mode
- **Interface:** USB 3.0
- **Wireless Security:** WEP, WPA/WPA2/WPA3, WPA-PSK/WPA2-PSK△
- **Modulation Technology:** DBPSK, DQPSK, CCK, OFDM, 16-QAM, 64-QAM, 256-QAM, 1024QAM

Specifications

Hardware

- Antennas: 2× High-Gain Dual-Band Antennas
- Dimensions: 30.5 × 14.8 × 111.7 mm (1.2 × 0.58 × 4.4 in)

Others

· Package Contents

AX3000 High Gain Wireless USB Adapter Archer TX50UH
Quick Installation Guide
USB 3.0 Cradle

· Certification

FCC, IC, RoHS

· System Requirements

Windows 10/11(64-bit) §

· Environment

Operating Temperature: 0°C~40°C (32°F ~104°F)
Operating Humidity: 10%~90% non-condensing
Storage Humidity: 5%~90% non-condensing



For more information, please visit

<https://www.tp-link.com/products/details/?model=Archer+TX50UH>

or scan the QR code left

©2023 TP-Link

†Maximum wireless signal rates are the physical rates derived from IEEE Standard 802.11 specifications. Actual wireless data throughput, wireless coverage, and number of connected devices are not guaranteed and will vary as a result of network conditions, AP limitations, and environmental factors, including building materials, obstacles, volume and density of traffic, and AP location.

‡Use of Wi-Fi 6 (802.11ax), and features including OFDMA, MU-MIMO, 1024-QAM, or HE160 require APs to also support the corresponding features.

§Functionality of Archer TX50UH may be restricted on some operating systems and platforms. Please try to update the device's driver for feature compatibility.

ΔUse of WPA3 requires APs to also support the corresponding feature.