

### **Product Highlights**

#### Wireless AC and Ethernet

Get the most out of your broadband connection by enjoying high-bandwidth applications like HD, 4K, and 3D video anywhere in your home

#### **Dual-band Wi-Fi for Seamless Performance**

Two concurrent wireless networks for higher bandwidth, improved range, and backward compatibility

**Mesh Ready** 

Supports Easy Mesh



### **DIR-812M**

# **AC1200 Dual Band Wi-Fi Router**

#### **Features**

#### **High-Speed Connectivity**

- 802.11ac MU-MIMO wireless delivers blazing fast wireless connectivity with increased range and reliability
- 1 x 10/100 Ethernet WAN port for fast paced Internet access
- 3 x 10/100 Ethernet LAN ports give you high-speed wired connectivity

#### Secure Wireless Connection

• Supports the latest WPA/WPA2/WPA3 Encryption

#### Flexible Bandwidth

- Concurrent dual-band wireless for connections up to 1200 Mbps¹
- · Client bandwidth management
- Beamforming

### Setup and Management

- Multiple Operating Modes Router / Access Point / Repeater / Wi-Fi Client
- Web browser-based setup and configuration
- Intuitive setup wizard to guide you through the configuration process
- Firewall and access control options to prevent attacks and restrict access to your network

The DIR-812M AC1200 MU-MIMO Wi-Fi Router is a powerful wireless networking solution designed for Small Office/Home Office (SOHO) environments. By combining high-speed 802.11ac Wi-Fi with dual-band technology and Ethernet ports, the DIR-812M provides a seamless networking experience with a high degree of convenience and flexibility for SOHOs. The DIR-812M's SOHO-class advanced security features keep data safe from unwanted network intruders. This together with the increased range and reliability of Wireless AC technology, helps provide a safe and secure network for devices further into your home or office.

### **High-Speed Wired and Wireless Connectivity**

The DIR-812M AC1200 MU-MIMO Wi-Fi Router upgrades your network to the latest high-speed wireless technology to bring you lightning-fast Wi-Fi speeds of up to 1200 Mbps¹ so you can meet the ever-greater demand from multimedia applications. Enjoy seamless high definition streaming media, Internet phone calls, online gaming, and content-rich web surfing throughout your home or office. The new DIR-812M AC 1200 Dual Band Wi-Fi Router also offers a built-in Wireless repeater mode and by combining two or more DIR-812M's can be set up to function as a Mesh solution. In addition, 10/100/1000 Ethernet ports give you solid, dependable wired performance for devices such as Network-Attached Storage (NAS), media centers, and gaming consoles.

#### **Dual-Band Wireless for Seamless Performance**

The DIR-812M AC1200 Dual Band Wi-Fi Router features dual-band wireless, allowing you to operate two concurrent, high-speed Wi-Fi bands for ultimate wireless performance. Surf the web or make important Internet phone calls on the 2.4 GHz band, while simultaneously streaming digital media on the 5 GHz band. What's more, each band can operate as a separate Wi-Fi network, giving you the ability to customize your network according to your connectivity needs. You can even configure a guest zone to give visitors Internet access without compromising the security of your SOHO network.



# **DIR-812M AC1200 Dual Band Wi-Fi Router**

# Easy to Set Up and Secure

Sharing your Internet connection doesn't have to be a complicated process - just open a web browser to access the setup wizard and follow the easy step-by-step instructions to get started. Configure, apply, and set up wireless security in minutes with the wireless network setup wizard, or use Wi-Fi Protected Setup (WPS), which establishes a secure connection to new devices without the need to enter settings or create passwords.

# Security

The wireless router DIR-825M includes a built-in firewall. The advanced security functions minimize threats of hacker attacks, preventing unwanted intrusions to your network, and blocking access to unwanted websites for users of your LAN.

General		
Device Interface	• 2 x RJ45 10M/100M LAN Ethernet interfaces 1 x RJ45 10M/100M WAN Ethernet interfaces	
	1 x Power Led 1 x Internet Led (red and green)	
	1 x Reset button(WPS button) 1 x Power Jack	
	1x wifi Led 1 x ETH Led	
Antenna	4 x 5dBi external antenna	
Power connector	Power input connector (DC)	
Functionality		
WAN connection types	<ul><li>PPPoE</li><li>Static IP</li><li>Dynamic IP</li></ul>	
Network functions	<ul><li>DHCP server/client</li><li>Dynamic DNS</li><li>Static routing</li></ul>	
Firewall functions	<ul> <li>Network Address Translation (NAT)</li> <li>Stateful Packet Inspection (SPI)</li> <li>URL filter</li> <li>MAC filter</li> <li>IP filtering</li> </ul>	<ul> <li>Port filtering</li> <li>DMZ and Port forwarding(Virtual server)</li> <li>NAPT and ALG</li> <li>Denial of Service (DoS) protection</li> </ul>
Management	<ul> <li>Firmware update via web-based interface</li> <li>Saving/restoring configuration to/from file</li> <li>Access settings through WEB GUI</li> <li>Automatic NTP Date/time from Internet Time S</li> <li>Logs and statistics</li> <li>IPSec/PPTP/L2TP pass-through</li> <li>Support TR-069*</li> </ul>	erver



# **DIR-812M AC1200 Dual Band Wi-Fi Router**

Wireless Parameters		
Standards	• IEEE 802.11 a/b/g/n/ac	
Frequency & Maximum Output Power	<ul> <li>11N: 2.4~2.4835GHz</li> <li>2.4GHz: 20dBm</li> <li>5GHz: 23dBm</li> </ul>	
Wireless connection security	<ul> <li>WPA/WPA2/WPA3 Encryption</li> <li>MAC filter</li> <li>WPS</li> </ul>	
Advanced functions	<ul> <li>Wireless Client Mode</li> <li>Wireless AP Mode</li> <li>Wireless Repeater Mode</li> <li>Multiple SSID's</li> <li>Wireless Schedule</li> </ul>	
Physical Parameters		
Dimensions	• 105*105*31.5mm	
Operating Environment		
Power	• Input: 12V DC, 1A	
Temperature	<ul> <li>Operating: 0 ~ 40 degrees °C</li> <li>Storage: -20 ~ 70 degrees °C</li> </ul>	
Humidity	• Operating: 10 ~ 90% (non-condensing) Storage: 5 ~ 95% (non-condensing)	
Order Information		
Part Number	Description	
DIR-812M	AC1200 Dual Band Wi-Fi Router	

 $<sup>\</sup>ensuremath{^*}$  with supported firmware version